## Digital output module CPX-AP-A-8DO-PI Part number: 8129107



X0	.0 .1.2.3	8	X1
X2			Х3
X4			X5
X6	.0 .1 .2 .3		X7

## **Data sheet**

Feature	Value
Dimensions (W x L x H)	(incl. interlinking block) 50.1 mm x 107.3 mm x 57.5 mm
Grid dimension	50.1 mm
Type of mounting	Screw-clamped
Product weight	98 g
Mounting position	optional
Ambient temperature	-20 °C50 °C
Note on ambient temperature	Observe ambient temperature derating according to IEC 61131-2:2017
Storage temperature	-20 °C70 °C
Relative air humidity	5 - 95% Non-condensing
Nominal altitude of use	<= 2000 m ASL (> 79.5 kPa)
Max. installation height	3500 m
Note on max. installation height	> 2000 m ASL (< 79.5 kPa) Observe ambient temperature derating according to IEC 61131-2:2017
Corrosion resistance class CRC	1 - Low corrosion stress
Vibration resistance	Transport application test with severity level 2 to FN 942017-4 and EN 60068-2-6
Note on vibration resistance	SG1 on H-rail SG2 on direct mounting Transport application test with severity class 1 to FN 942017-4 and EN 60068-2-6
Shock resistance	Shock test with severity level 2 to FN 942017-5 and EN 60068-2-27
Note on shock resistance	30 g/11 ms to EN 60068-2-27 SG1 on H-rail SG2 on direct mounting Shock test with severity level 1 to FN 942017-5 and EN 60068-2-27
Protection class	
Pollution degree	2
Overvoltage category	11

Feature	Value		
Max. cable length	30 m outputs		
LABS (PWIS) conformity	VDMA24364-B2-L		
Fire test material	UL94 V-0 (housing)		
Note on materials	RoHS-compliant Free of halogen Free of phosphoric acid ester		
Material cover	PBT-reinforced		
Material screws	Nickel-plated steel		
Material o-ring	FPM		
Diagnostics via LED	Diagnostics per channel Diagnostics per module Load power supply Status per channel		
Diagnostics per internal communication	Load switch-off Communication fault Short-circuit/overload in output signal Electronics/sensors overvoltage Load overvoltage Electronics/sensors undervoltage Load undervoltage		
Max. address volume, outputs	1 Byte		
Number of outputs	8		
Module parameters	Configuration of voltage monitoring load supply PL Behaviour after short circuit/overload at analogue output		
Communication interface, protocol	AP		
Note regarding operating voltage	SELV/PELV fixed power supplies required Note voltage drop		
Note on nominal operating voltage DC	Protected Extra-Low-Voltage to IEC 60204-1		
Nominal operating voltage DC of load	24 V		
Permissible voltage fluctuation of load	± 25 %		
Nominal DC operating voltage, electronics/sensors	24 V		
Permissible voltage fluctuations for electronics/sensors	± 25%		
Intrinsic current consumption at nominal operating voltage for electronics/sensors	Typically 40 mA		
Intrinsic current consumption at nominal operating voltage load	Typically 5 mA		
Power failure bridging	10 ms		
Potential separation between the supply voltages electronics/sensor technology and load/valves	Yes		
Reverse polarity protection	yes		
Electrical connection output, function	Digital output		
Electrical connection output, connection type	8x terminal strip		
Electrical connection output, connector system	Spring-loaded terminal		
Electrical connection output, number of connections/cores	4		
Electrical connection for output, conductor cross section	0.25 mm <sup>2</sup> 1.5 mm <sup>2</sup>		
Electrical connection for output, note on conductor cross section	0.13 - 1.5 mm <sup>2</sup> for flexible conductors without wire ferrule		
Electrical connection for output, AWG conductor cross section	AWG24 - AWG16		
Characteristic for outputs	According to IEC 61131-2, type 0.5		
Switching logic for outputs	PNP (positive switching)		
Fuse protection of outputs (short circuit)	Internal electronic fuse per channel		
Behaviour after end of overload of the outputs	No automatic return		
Output delay with ohmic load	Signal change 0->1: < 200 μs Signal change 1->0: < 200 μs		
Max. residual current outputs per module	4 A		
Electrical isolation of outputs between channels	no		
Electrical isolation of outputs between channel - internal communication	yes		
Max. power supply per channel	0.5 A		