

Multi-axis controllers CMXR

FESTO



Multi-axis controllers CMXR

Key features

At a glance

Powerful – reducing cycle times with optimum motion

Reducing cycle times is a requirement of all customers. There are limits, however, to what is possible based on, for example, the mechanical system, the travel distances or the maximum forces acting on a workpiece.

The challenge is to be quick and at the same time protect the mechanical system. The multi-axis controller CMXR offers the following features:

- Motion path smoothing
- Ramp shapes for acceleration
- Constant path speed

Economical – reducing costs with easy configuration

Reducing costs is always an important issue. The Festo Configuration Tool (FCT) in combination with the programming language Festo Teach Language (FTL) makes configuration quick and easy and significantly shortens configuration times.

This enables the full focus to be on developing the application, since the basic motion programs are contained in the CMXR. The FTL programming tool utilises these basic programs. The FTL programs can therefore be used immediately.

Reliable – easy handling of tools in three dimensions

The flange is not the end of a kinematic system. Mounted on the flange are the tools, which can, for example, comprise pneumatic drives such as the semi-rotary drive DRQD. Tools oriented other than vertically are a challenge for a controller. The CMXR enables the end position of the tool, for example a vacuum suction cup, to be defined three-dimensionally and

transfers this point to the programmed path. This feature also makes it easy to move the three-dimensionally positioned tool in the direction of the tool's path simply by pressing a button on the teach pendant CDSA. The teach-in of positions on parts slides, for example, is thus very easy and efficient.

Reliable – easy integration with finished interfaces

The CMXR system offers fully defined interfaces for actuation via an external controller. This can be done with a simple method using digital signals or via a Profibus. These interfaces enable programs to be selected, started or stopped, for example. The Profibus variant also offers the option of reading or writing variables from the CMXR controller.

This transfer of variables enables movements to be influenced or even coupled with a process running on the external controller. To minimise the complexity when using an external PLC, modules for the PLC systems Siemens Simatic S7 and systems based on CoDeSys V2.3 are supplied for actuation via Profibus.

Flexible – from simple to complex kinematic systems

Cartesian system



Tripod



The multi-axis controller CMXR is the heart of a complete kinematic system solution. It combines a mechanical system, electrical drive technology and control technology into a complete motion control package with integrated and harmonised interfaces for all system components involved.


The multi-axis controller enables simple axis movements, from point to point to complex path control. It is able to control simple and complex kinematic systems with up to 6 degrees of freedom in three dimensions. These include, among others, linear and three-dimensional gantries (Cartesian systems) as well as tripod kinematic systems.

Multi-axis controllers CMXR

Key features

At a glance

Convenient – quick and easy configuration



Transparent – programming in plain text with FTL

Via teach pendant CDSA



Convenient – easy programming via teach-in



Via Festo Configuration Tool (FCT)



When creating a motion program, the motion sequence is very often known but not the precise position to be approached, for example of a gripper or a tray. These can only be determined directly during commissioning by means of accurate approaching. The CMXR in combination with the teach pendant CDSA offers dialogue-based software for this purpose, thus enabling quick and easy teach-in of the necessary positions.

The main requirements for product configuration software are speed, reliability and user-friendliness. The multi-axis controller CMXR, like other products from Festo, is configured via the Festo Configuration Tool (FCT). Electrical variables (e.g. inputs and

outputs) as well as mechanical variables (e.g. choice of the kinematic system) are defined in the configuration. The sophisticated user guidance system guarantees quick and easy configuration of the complex multi-axis system.

The motion programs are programmed using the text-based macro programming tool of the Festo Teach Language (FTL). This powerful programming tool contains macros, for example for movements, dynamic settings up to I/O processing of peripheral devices

such as grippers, for example, and has been specially developed for the CMXR. Programming can be done online via the teach pendant CDSA or offline via the FTL programming editor. The FTL editor is integrated in the Festo Configuration Tool (FCT).

Flexible – mobile operation and monitoring with CDSA




The teach pendant CDSA features an emergency stop switch as well as a 3-stage enabling key. Both devices are designed with two channels and are prepared for integration in the customer's safety circuits. The purpose of the enabling key is to approve the drive power during set-up. In addition to the hardware and ergonomic handle, the CDSA also features a colour touch screen as an alternative to the keypad for starting actions.

Multi-axis controllers CMXR

Key features

FESTO

Everything from a single source – perfectly co-ordinated




Multi-axis controllers CMXR


Key features

Application examples


Removing and palletising workpieces



Handling and picking carrier trays




Feeding workpieces with simultaneous quality inspection via a vision system



Multi-axis controllers CMXR

Peripherals overview

FESTO



Multi-axis controllers CMXR


Peripherals overview

Accessories			➔ Page/Internet
Type	Brief description		
[1] Retainer CAFM	Wall fixture for the teach pendant CDSA with cable suspension	22	
[2] Teach pendant CDSA	For operating, monitoring and programming the multi-axis controller CMXR-C1	20	
[3] Interface housing CAMI	Adapter for connecting the teach pendant CDSA outside a control cabinet with the controller CMXR inside a control cabinet	23	
[4] Multi-axis controller CMXR	Enables simple axis movements, from point to point to complex path control	9	
[5] Motor controller CMM...	For controlling stepper or servo motors from Festo via a CAN interface	cmm	
[6] Three-dimensional gantry	Wide range of kinematic systems within the multi-axis modular system from Festo	three-dimensional gantry	
[7] Valve terminal	The multi-axis controller enables the connection of peripheral devices, for example valve terminals, via a CAN interface	valve terminal	
- Cables and plugs	Connecting cables and plugs for connecting the individual devices	23	

Multi-axis controllers CMXR

Peripherals overview and type codes

Controller CMXR-C1 with peripheral modules



Peripheral modules	Brief description	➔ Page/Internet
Input/output module, digital CECX-D-8E8A-NP-2	<ul style="list-style-type: none"> • 8 digital inputs • 8 digital outputs 	12
Input module, digital CECX-D-16E	<ul style="list-style-type: none"> • 16 digital inputs 	14
Output module, digital CECX-D-14A-2	<ul style="list-style-type: none"> • 14 digital outputs 	15
Input/output module, analogue CECX-A-4E4A-V	<ul style="list-style-type: none"> • 4 analogue voltage inputs • 4 analogue voltage outputs 	16
Input/output module, analogue CECX-A-4E4A-A	<ul style="list-style-type: none"> • 4 analogue current inputs • 4 analogue current outputs 	16
Encoder interface CECX-C-2G2	<ul style="list-style-type: none"> • 2 encoder interfaces 	18
Fieldbus interface CECX-F-PB-S-VO	<ul style="list-style-type: none"> • Profibus slave DP-VO 	19

- Note

- Plugs are not included in the scope of delivery for the peripheral modules (plugs ➔ 23)
- Max. 1 Profibus slave module can be used
- Max. 8 peripheral modules can be used

Additional product information
➔ www.festo.com

Type codes

CMXR	-	C1
Type		
CMXR	Multi-axis controller	
Controller		
C1	Controller 1	

Multi-axis controllers CMXR

Technical data

Controller
CMXR-C1



General technical data

Operating voltage range	[V DC]	19.2 ... 30
Nominal operating voltage	[V DC]	24
Power consumption at 24 V	[W]	14
Max. power consumption	[W]	69
Max. protection	[A]	10
Type of mounting		On H-rail (TS 35x7.5)
Controller operating mode		Manual
Operating elements		CTRL button
Status display		7-segment display LED green = power
Supported kinematic systems		2-axis gantries 3-axis gantries Any interpolation Tripod
Total number of axes		6
Breakdown of the axes		3 basic axes 3 auxiliary axes 1 manual axis
CPU data		64 MB DRAM 400 MHz processor
Memory card		Compact Flash ≥ 128 MB
Control methods		I/O standalone I/O (16I/16O) I/O + Profibus DP Profibus DP
Program organisation		Via FTL programs
Configuration support		FCT (Festo Configuration Tool)
Command set		Mathematical functions
Max. number of commands		Approx. 1,500
Programming software		FCT (Festo Configuration Tool) CDSA-D1-VX
Programming language		FTL (Festo Teach Language) Text-based macro language
USB interface		USB 1.1
Protection class		III
Product weight	[g]	580
Materials		
Note on materials		Contains PWIS (paint-wetting impairment substances) RoHS-compliant

Multi-axis controllers CMXR

Technical data

FESTO

Technical data – Interfaces

Ethernet

Connector plug	RJ45 socket, 8-pin
Transmission speed [Mbps]	10/100
Supported protocols	TCP/IP


Fieldbus interface

Type	CAN bus
Number	2x CANopen masters
Connection technology	Sub-D plug, 9-pin
Max. fieldbus transmission rate [Mbps]	1 Can be set via software
Electrical isolation	No

Operating and environmental conditions


Ambient temperature [°C]	5 ... 55
Storage temperature [°C]	-40 ... +70
Resistance to shock	EN 60068-2-27 EA 15 g, 11 ms (half-sine)
Resistance to vibration	EN 60068-2-6-FC 5 ... 9 Hz 3.5 mm 9 ... 150 Hz 1g
Relative air humidity [%]	10 ... 95
Protection class	IP20
CE mark (see declaration of conformity)	To EU EMC Directive
Certification	cULus Listed (OL) C-Tick


Dimensions



Multi-axis controllers CMXR

Technical data

Ordering data	
Controller	Part No. Type
	552095 CMXR-C1

Ordering data – Documentation ¹⁾			
	Language	Part No.	Type
		System manual	Programming manual
	DE	560309 GDCP-CMXR-SY-DE	560315 GDCP-CMXR-SW-DE
	EN	560310 GDCP-CMXR-SY-EN	560316 GDCP-CMXR-SW-EN
	ES	560311 GDCP-CMXR-SY-ES	560317 GDCP-CMXR-SW-ES
	FR	560312 GDCP-CMXR-SY-FR	560318 GDCP-CMXR-SW-FR
	IT	560313 GDCP-CMXR-SY-IT	560319 GDCP-CMXR-SW-IT
	SV	560314 GDCP-CMXR-SY-SV	560320 GDCP-CMXR-SW-SV
		Hardware manual	Control interface manual
	DE	560321 GDCP-CMXR-HW-DE	560327 GDCP-CMXR-F-DE
	EN	560322 GDCP-CMXR-HW-EN	560328 GDCP-CMXR-F-EN
	ES	560323 GDCP-CMXR-HW-ES	560329 GDCP-CMXR-F-ES
	FR	560324 GDCP-CMXR-HW-FR	560330 GDCP-CMXR-F-FR
	IT	560325 GDCP-CMXR-HW-IT	560331 GDCP-CMXR-F-IT
	SV	560326 GDCP-CMXR-HW-SV	560332 GDCP-CMXR-F-SV

1) User manual in paper form is not included in the scope of delivery

Multi-axis controllers CMXR

Technical data

FESTO

Input/output module,
digital
CECX-D-8E8A-NP-2



General technical data

Operating voltage range	[V DC]	19.2 ... 30
Nominal operating voltage	[V DC]	24
Electrical connection technology for I/O		Socket strip, grid 5.08 mm
Power consumption at 5 V	[W]	0.4
Power consumption at 24 V	[W]	1.9
Protection class		III
Product weight	[g]	135
Materials		
Note on materials		Contains PWIS (paint-wetting impairment substances)
		RoHS-compliant


Technical data

Digital inputs		
Number		8
Fast clock pulse inputs		2, interruptible, response time 50 µs
Input voltage	[V DC]	24
Nominal value for FALSE	[V DC]	≤ 5
Nominal value for TRUE	[V DC]	≥ 15
Input signal delay	[ms]	20, 100, adjustable
	[kHz]	12 with interrupt input
Electrical isolation		Yes, via optocoupler
Status display		Green LED
Switching logic		NPN (negative switching)
Digital outputs		
Number		8
Contact		Transistor
Output voltage	[V DC]	24
Output current	[A]	2 with 50% concurrence
Short circuit proof		Yes
Electrical isolation		Yes, via optocoupler
Status display		Orange LED
Switching logic		PNP (positive switching)

Multi-axis controllers CMXR

Technical data

Operating and environmental conditions		
Ambient temperature	[°C]	5 ... 55
Storage temperature	[°C]	-40 ... +70
Resistance to shock		EN 60068-2-27 EA 15 g, 11 ms (half-sine)
Resistance to vibration		EN 60068-2-6-FC 5 ... 9 Hz 3.5 mm 9 ... 150 Hz 1g
Relative air humidity	[%]	10 ... 95
Protection class		IP20
Certification		cULus Listed (OL)

Ordering data				
Input/output module, digital	Documentation ¹⁾			
Part No.	Type	Language	Part No.	Type
	552099 CECX-D-8E8A-NP-2		DE	560585 GDCC-CECX-D-8E8A-NP-DE
		EN	560586 GDCC-CECX-D-8E8A-NP-EN	
		ES	560587 GDCC-CECX-D-8E8A-NP-ES	
		FR	560588 GDCC-CECX-D-8E8A-NP-FR	
		IT	560589 GDCC-CECX-D-8E8A-NP-IT	
		SV	560590 GDCC-CECX-D-8E8A-NP-SV	

1) User manual in paper form is not included in the scope of delivery

Multi-axis controllers CMXR

Technical data

Input module,
digital
CECX-D-16E



General technical data

Electrical connection technology for I/O	Socket strip, grid 5.08 mm
Power consumption at the system bus [W]	0.4
Protection class	III
Product weight [g]	130

Materials

Note on materials	Contains PWIS (paint-wetting impairment substances) RoHS-compliant
-------------------	---


Technical data

Digital inputs	
Number	16
Fast clock pulse inputs	2, interruptible, response time 100 µs
Input voltage [V DC]	24
Nominal value for FALSE [V DC]	≤ 5
Nominal value for TRUE [V DC]	≥ 15
Input signal delay [ms]	20, 200, adjustable
	Additionally 0.2 ms with interrupt inputs
Electrical isolation	Yes, via optocoupler
Status display [V DC]	LED

Operating and environmental conditions

Ambient temperature [°C]	5 ... 55
Storage temperature [°C]	-40 ... +70
Resistance to shock	EN 60068-2-27 EA 15 g, 11 ms (half-sine)
Resistance to vibration	EN 60068-2-6-FC 5 ... 9 Hz 3.5 mm 9 ... 150 Hz 1g
Relative air humidity [%]	10 ... 95
Protection class	IP20
Certification	cULus Listed (OL)

Ordering data

Input module, digital	Part No.	Type	Documentation ¹⁾			
			Language	Part No.	Type	
	552096	CECX-D-16E		DE	560573	GDCC-CECX-D-16E-DE
				EN	560574	GDCC-CECX-D-16E-EN
				ES	560575	GDCC-CECX-D-16E-ES
				FR	560576	GDCC-CECX-D-16E-FR
				IT	560577	GDCC-CECX-D-16E-IT
				SV	560578	GDCC-CECX-D-16E-SV

1) User manual in paper form is not included in the scope of delivery

Multi-axis controllers CMXR

Technical data

Output module,
digital
CECX-D-14A-2



General technical data

Operating voltage range	[V DC]	19.2 ... 30
Nominal operating voltage	[V DC]	24
Electrical connection technology for I/O		Socket strip, grid 5.08 mm
Power consumption at the system bus	[W]	0.4
Protection class		III
Product weight	[g]	135
<hr/>		
Materials		
Note on materials		Contains PWIS (paint-wetting impairment substances) RoHS-compliant

Technical data

Digital outputs	
Number	14
Contact	Transistor
Output voltage	[V DC]
Output current	[A]
Short circuit proof	Yes
Electrical isolation	Yes, via optocoupler
Electrical isolation in groups	Yes, in 2 groups
Status display	[V DC]
	LED

Operating and environmental conditions

Ambient temperature	[°C]	5 ... 55
Storage temperature	[°C]	-40 ... +70
Resistance to shock		EN 60068-2-27 EA 15 g, 11 ms (half-sine)
Resistance to vibration		EN 60068-2-6-FC 5 ... 9 Hz 3.5 mm 9 ... 150 Hz 1g
Relative air humidity	[%]	10 ... 95
Protection class		IP20
Certification		cULus Listed (OL)

Ordering data

Output module, digital	Part No.	Type	Documentation ¹⁾	Language			Part No.	Type	
				DE	EN	ES			
	552097	CECX-D-14A-2		560579	560580	560581	GDCC-CECX-D-14A-DE	GDCC-CECX-D-14A-EN	GDCC-CECX-D-14A-ES
				560582	560583	560584	GDCC-CECX-D-14A-FR	GDCC-CECX-D-14A-IT	GDCC-CECX-D-14A-SV

1) User manual in paper form is not included in the scope of delivery

Multi-axis controllers CMXR

Technical data

FESTO

Input/output module,
analogue
CECX-A-4E4A





General technical data		
	CECX-A-4E4A-V	CECX-A-4E4A-A
Variant	Voltage inputs/outputs	Current inputs/outputs
Electrical connection technology for I/O	Socket strip, grid 5.08 mm	
Power consumption at 5 V [W]	0.3	0.3
Power consumption at 24 V [W]	3.3	3.6
Protection class	III	
Product weight [g]	135	
Materials		
Note on materials	Contains PWIS (paint-wetting impairment substances) RoHS-compliant	

Technical data		
	CECX-A-4E4A-V	CECX-A-4E4A-A
Analogue inputs		
Number	4	4
Resolution [bit]	14	14
Signal range [V]	0 ... 10 Vref	-
	±10	-
	[mA]	0 ... 20
	-	4 ... 20
Value of the least significant bit (LSB)	[mV]	-
	[µA]	1.35
Supply voltage for actuators	[V DC]	10 ±2.5 % (max. 20 mA)
Input resistance	[Ω]	10x10 ⁶
Absolute accuracy at 25 °C	[%]	±0.01
Sampling repeat time	[ms]	1
Electrical isolation		No
Analogue outputs		
Number	4	4
Resolution [bit]	12	12
Max. load resistance [Ω]	≥ 1 000	≤ 600
Signal range [V]	±10	-
	[mA]	0 ... 20
Value of the least significant bit (LSB)	[mV]	-
	[µA]	5.39
Conversion time	[ms]	1
Absolute accuracy at 25 °C	[%]	±0.15

Multi-axis controllers CMXR

Technical data

Operating and environmental conditions		
Ambient temperature	[°C]	5 ... 55
Storage temperature	[°C]	-40 ... +70
Resistance to shock		EN 60068-2-27 EA 15 g, 11 ms (half-sine)
Resistance to vibration		EN 60068-2-6-FC 5 ... 9 Hz 3.5 mm 9 ... 150 Hz 1g
Relative air humidity	[%]	10 ... 95
Protection class		IP20
Certification		cULus Listed (OL)

Ordering data																							
Input/output module, analogue		Documentation ¹⁾																					
Part No.	Type	Language	Part No.	Type																			
	<table border="1"> <thead> <tr> <th>Voltage inputs/outputs</th> </tr> </thead> <tbody> <tr> <td>552100 CECX-A-4E4A-V</td> </tr> </tbody> </table> <table border="1"> <thead> <tr> <th>Current inputs/outputs</th> </tr> </thead> <tbody> <tr> <td>552101 CECX-A-4E4A-A</td> </tr> </tbody> </table>	Voltage inputs/outputs	552100 CECX-A-4E4A-V	Current inputs/outputs	552101 CECX-A-4E4A-A		<table border="1"> <thead> <tr> <th>Voltage inputs/outputs</th> </tr> </thead> <tbody> <tr> <td>DE 560591 GDCC-CECX-A-4E4A-V-DE</td> </tr> <tr> <td>EN 560592 GDCC-CECX-A-4E4A-V-EN</td> </tr> <tr> <td>ES 560593 GDCC-CECX-A-4E4A-V-ES</td> </tr> <tr> <td>FR 560594 GDCC-CECX-A-4E4A-V-FR</td> </tr> <tr> <td>IT 560595 GDCC-CECX-A-4E4A-V-IT</td> </tr> <tr> <td>SV 560596 GDCC-CECX-A-4E4A-V-SV</td> </tr> </tbody> </table> <table border="1"> <thead> <tr> <th>Current inputs/outputs</th> </tr> </thead> <tbody> <tr> <td>DE 560597 GDCC-CECX-A-4E4A-A-DE</td> </tr> <tr> <td>EN 560598 GDCC-CECX-A-4E4A-A-EN</td> </tr> <tr> <td>ES 560599 GDCC-CECX-A-4E4A-A-ES</td> </tr> <tr> <td>FR 560600 GDCC-CECX-A-4E4A-A-FR</td> </tr> <tr> <td>IT 560601 GDCC-CECX-A-4E4A-A-IT</td> </tr> <tr> <td>SV 560602 GDCC-CECX-A-4E4A-A-SV</td> </tr> </tbody> </table>	Voltage inputs/outputs	DE 560591 GDCC-CECX-A-4E4A-V-DE	EN 560592 GDCC-CECX-A-4E4A-V-EN	ES 560593 GDCC-CECX-A-4E4A-V-ES	FR 560594 GDCC-CECX-A-4E4A-V-FR	IT 560595 GDCC-CECX-A-4E4A-V-IT	SV 560596 GDCC-CECX-A-4E4A-V-SV	Current inputs/outputs	DE 560597 GDCC-CECX-A-4E4A-A-DE	EN 560598 GDCC-CECX-A-4E4A-A-EN	ES 560599 GDCC-CECX-A-4E4A-A-ES	FR 560600 GDCC-CECX-A-4E4A-A-FR	IT 560601 GDCC-CECX-A-4E4A-A-IT	SV 560602 GDCC-CECX-A-4E4A-A-SV		
Voltage inputs/outputs																							
552100 CECX-A-4E4A-V																							
Current inputs/outputs																							
552101 CECX-A-4E4A-A																							
Voltage inputs/outputs																							
DE 560591 GDCC-CECX-A-4E4A-V-DE																							
EN 560592 GDCC-CECX-A-4E4A-V-EN																							
ES 560593 GDCC-CECX-A-4E4A-V-ES																							
FR 560594 GDCC-CECX-A-4E4A-V-FR																							
IT 560595 GDCC-CECX-A-4E4A-V-IT																							
SV 560596 GDCC-CECX-A-4E4A-V-SV																							
Current inputs/outputs																							
DE 560597 GDCC-CECX-A-4E4A-A-DE																							
EN 560598 GDCC-CECX-A-4E4A-A-EN																							
ES 560599 GDCC-CECX-A-4E4A-A-ES																							
FR 560600 GDCC-CECX-A-4E4A-A-FR																							
IT 560601 GDCC-CECX-A-4E4A-A-IT																							
SV 560602 GDCC-CECX-A-4E4A-A-SV																							

1) User manual in paper form is not included in the scope of delivery

Multi-axis controllers CMXR

Technical data

FESTO

Encoder interface
CECX-C-2G2



General technical data

Operating voltage range	[V DC]	19.2 ... 30
Nominal operating voltage	[V DC]	24
Electrical connection technology for I/O		Socket strip, grid 5.08 mm
Power consumption at 5 V	[W]	0.6
Protection class		III
Product weight	[g]	135
Materials		
Note on materials		Contains PWIS (paint-wetting impairment substances) RoHS-compliant

Technical data – Interfaces

Digital inputs		
Fast clock pulse inputs		2 (latch function) response time 20 µs NPN/PNP
Electrical isolation		No
Encoder inputs		
Number		2
Connection technology		Sub-D socket, 9-pin
Resolution	[bit]	Speed measurement: 32
	[bit]	Distance measurement: 24
Transmitter supply voltage	[V DC]	24
	[V DC]	5.05 ±4 % (100 mA/channel)
Max. input frequency	[kHz]	250
Signal range	[V]	5 differential (RS422)
	[V]	24 single-ended

Operating and environmental conditions

Ambient temperature	[°C]	5 ... 55
Storage temperature	[°C]	-40 ... +70
Resistance to shock		EN 60068-2-27 EA 15 g, 11 ms (half-sine)
Resistance to vibration		EN 60068-2-6-FC 5 ... 9 Hz 3.5 mm 9 ... 150 Hz 1g
Relative air humidity	[%]	10 ... 95
Protection class		IP20
Certification		cULus Listed (OL)

Ordering data

Encoder interface	Part No.	Type	Documentation ¹⁾	Language	Part No.	Type
				DE	560603	GDCC-CECX-C-2G2-DE
	552117	CECX-C-2G2		EN	560604	GDCC-CECX-C-2G2-EN
				ES	560605	GDCC-CECX-C-2G2-ES
				FR	560606	GDCC-CECX-C-2G2-FR
				IT	560607	GDCC-CECX-C-2G2-IT
				SV	560608	GDCC-CECX-C-2G2-SV

1) User manual in paper form is not included in the scope of delivery

Multi-axis controllers CMXR

Technical data

Fieldbus interface,
Profibus slave DP-V0
CECX-F-PB-S-V0



General technical data

Power consumption at 5 V	[W]	1.4
Status displays	LED (status)	
	LED red = bus fault	
Protection class		III
Product weight	[g]	140
Materials		
Note on materials	Contains PWIS (paint-wetting impairment substances)	
	RoHS-compliant	

Technical data – Interface

Fieldbus	
Type	Profibus slave DP-V0
Connection technology	Sub-D socket, 9-pin
Transmission rate	9.6 kbps ... 12 Mbps
Electrical isolation	Yes

Operating and environmental conditions

Ambient temperature	[°C]	5 ... 55
Storage temperature	[°C]	-40 ... +70
Resistance to shock	EN 60068-2-27 EA	
	15 g, 11 ms (half-sine)	
Resistance to vibration	EN 60068-2-6-FC	
	5 ... 9 Hz 3.5 mm	
	9 ... 150 Hz 1g	
Relative air humidity	[%]	10 ... 95
Protection class		IP20
Certification		cULus Listed (OL)

Ordering data

Fieldbus interface, Profibus slave DP-V0	Part No.	Type	Documentation ¹⁾	Language	Part No.	Type
552102 CECX-F-PB-S-V0				DE	560567	GDCC-CECX-F-PB-S-V0-DE

1) User manual in paper form is not included in the scope of delivery

Multi-axis controllers CMXR

Accessories

FESTO

Teach pendant
CDSA-D1-VX




General technical data		
Operating voltage range	[V DC]	19 ... 30
Nominal operating voltage	[V DC]	24
Current consumption ¹⁾	[A]	0.4
User memory	[MB]	256
Display	Colour TFT	
Display size	6.5"	
Display resolution	VGA, 640x480 pixels	
Display properties	Touch screen	
Number of function keys	31	
Number of system LEDs	4	
Operating elements	2 enabler keys Emergency stop	
Area of application	Only with multi-axis controller CMXR-C1	
Ethernet interface	2 interfaces RJ45, 10/100 Mbps	
USB interface	Yes	
Backup battery	Yes	
Product weight	[g]	1,250
Materials		
Note on materials	Contains PWIS (paint-wetting impairment substances) RoHS-compliant	

1) At nominal operating voltage

Operating and environmental conditions		
Ambient temperature	[°C]	0 ... +50
Storage temperature	[°C]	-20 ... +70
Relative air humidity	[%]	5 ... 95
Protection class	IP65	
CE mark (see declaration of conformity)	To EU EMC Directive	


Multi-axis controllers CMXR

Accessories

DimensionsDownload CAD data ➔ www.festo.com**Ordering data**

	Part No.	Type
Teach pendant	552103	CDSA-D1-VX

Ordering data – Documentation¹⁾

	Language	Part No.	Type	Part No.	Type
		System manual		Software manual	
	DE	560333	GDCP-CDSA-SY-DE	560339	GDCP-CDSA-SW-DE
	EN	560334	GDCP-CDSA-SY-EN	560340	GDCP-CDSA-SW-EN
	ES	560335	GDCP-CDSA-SY-ES	560341	GDCP-CDSA-SW-ES
	FR	560336	GDCP-CDSA-SY-FR	560342	GDCP-CDSA-SW-FR
	IT	560337	GDCP-CDSA-SY-IT	560343	GDCP-CDSA-SW-IT
	SV	560338	GDCP-CDSA-SY-SV	560344	GDCP-CDSA-SW-SV

1) User manual in paper form is not included in the scope of delivery

Multi-axis controllers CMXR

Accessories


FESTO

Retainer
CAF-M-D1-W



Dimensions

Download CAD data → www.festo.com



Ordering data

	Part No.	Type
Retainer	552107	CAF-M-D1-W

Multi-axis controllers CMXR

Accessories

Interface housing

CAMI-C







General technical data

Type of mounting	On control cabinet wall (M25)
Mounting position	Any
Electrical connection	Ethernet interface: RJ45
	Coninver connector M25, 17-pin
	Spring force connector, 11-pin
Protection class	IP65 to IEC 60529
Dimensions	
Length [mm]	26
Width [mm]	67.2
Height [mm]	76.1
Materials	
Note on materials	Contains PWIS (paint-wetting impairment substances) RoHS-compliant

Ordering data

	Part No.	Type
Interface housing	552116	CAMI-C

Ordering data – Cables and plugs

	Brief description	Cable length [m]	Part No.	Type
	Connecting cable: between multi-axis controller CMXR and teach pendant CDSA via interface housing CAMI-C	5	552104	NESC-C-D1-5-C1
		10	552105	NESC-C-D1-10-C1
		15	552106	NESC-C-D1-15-C1
	Plug for interface housing CAMI-C, 11-pin	-	558328	NECC-L1G11-C1
	Plug for peripheral modules, 2-pin		553857	NECC-L1G2-C1
	Plug for peripheral modules, 4-pin		553858	NECC-L1G4-C1
	Plug for peripheral modules, 6-pin		553859	NECC-L1G6-C1
	Plug for peripheral modules, 8-pin		553860	NECC-L1G8-C1
	Plug for peripheral modules, 18-pin		553861	NECC-L1G18-C1
	Plug: is used to bridge the emergency stop circuit when the teach pendant is disconnected	-	555676	CAMF-B-M25-G4
	Plug: for Profibus interface; Sub-D, 9-pin, without terminating resistor	-	533780	FBS-SUB-9-WS-PB-K
	Plug: for CAN bus interface; Sub-D, 9-pin, without terminating resistor		533783	FBS-SUB-9-WS-CO-K