Air Barrier Sensors

Sender for Air Barrier Type SML-40-S



The sender nozzle may also be used as a back pressure sensor in combination with a separate air supply throttling system, (for example, Y-PK-3-D). See SD-2 setup shown on page 188.

The sender is used with receiver SFL-100-F (see page 202) or back pressure end stop SD-3 (see page 188) to set up an air barrier sensing arrangement (see illustrations on page 184). The sender nozzle produces a fine, stable flow of air, generating a dynamic pressure in the receiver. If an object interferes with the air flow, the receiver signal pressure decreases. For this combination, optimal sense range between the receiver and sender nozzle is 0.8-1.5 in / 20-40 mm. Air flowing from the two nozzles must be directed so that the critical point lies in front of the receiver orifice. For sensing ranges greater than 2 in / 50 mm, the flow of the receiver must be reduced by upstream throttling; for smaller sensing ranges, that of the sender must be reduced. The corresponding values are shown in the graph on page 201.

SML-40-S





Order Number Part No./Type	7442 SML-40-S		
Medium	Compressed air (filtered, unlubricated)		
Mounting	M12 x 1 threaded with mounting nuts		
Mounting Hole Diameter	0.5 in / 12.5 mm		
Connection	Barbed fitting for 3/16 in / 3 mm tubing		
Orifice Size	0.1 in / 2.5 mm		
Supply Pressure Range at P*	1.5 to 6 psi / 0.1 to 0.4 bar		
Signal Pressure Range at A	See graph, next page		
Air Consumption at 1.5 psi / 0.1 bar	0.22 SCFM / 6.3 I/min		
Max. Nozzle Range	2 in / 50 mm (no upstream throttling)		
Ambient Temperature	-40 to 212°F / -40 to 100°C†		
Design	Nozzle, no moving parts		
Material	Housing: Al, brass		
Weight	0.033 lb / 0.015 kg		

* 14 to 140°F / -10 to 60°C

† Depending on tubing used

Non-Contact Pneumatic Sensors

Dimensions and Mounting Hardware

FESTC

Type SML-40-S



Dimensions

а	0.99 in / 25 mm		
b	0.18 in / 4.5 mm	h	0.63 in / 16 mm
с	1.18 in / 30 mm	i	0.39 in / 10 mm
d	1.58 in / 40 mm	j	1.38 in / 35 mm
е	0.48 in / 12.1 mm	k	0.16 in / 4 mm
f	0.12 in / 3 mm	1	1.02 in / 26 mm
g	0.43 in / 11 mm	m	1.36 in / 34.5 mm

- Barbed fitting for 3/16 in / 3 mm tubing
- SW = wrench size, mm

Flange Mount Order Number 5129 FBN-8/10



Xⁱ

Order Number 5123 HBN-8/10-1

Foot Mount



Signal Pressure versus Sensing Range (at 2 psi / 150 mbar Supply Pressure, SML-40-S and SD-3).



- 1 No Upstream Throttling
- ② Upstream Throttling, Diameter 0.019 in / 0.5 mm
- ③ Upstream Throttling, Diameter 0.016 in / 0.4 mm
- ④ Upstream Throttling, Diameter 0.012 in / 0.3 mm
- ⑤ P Blocked
- 6 Upstream Throttling

Festo - Your Partner in Automation





1 Festo Inc.

5300 Explorer Drive Mississauga, ON L4W 5G4 Canada

Festo Customer Interaction Center Tel: 18774633786 Fax: 18773933786 Email: customer.service.ca@festo.com ventas.mexico@festo.com



2 Festo Pneumatic

Av. Ceylán 3, Col. Tequesquináhuac 54020 Tlalnepantla, Estado de México

Multinational Contact Center 01 800 337 8669



3 Festo Corporation 1377 Motor Parkway Suite 310 Islandia, NY 11749



4 **Regional Service Center** 7777 Columbia Road Mason, OH 45040

Festo Customer Interaction Center 1 800 993 3786 1 800 963 3786 customer.service.us@festo.com

Subject to change

f 🗾 in 🛗 www.festo.com/socialmedia

Connect with us



www.festo.com